



# 2014 UP RZR POWER CABLE KIT

## Installation Guide

---


Thank you for purchasing XTC's Power Cable Kit. The kit comes complete with everything needed for installation. The kit includes 8 Gauge power wire with a 50 Amp Circuit breaker for overall circuit protection . More installation information can be found at [www.xtcmotorsports.net/pp/install](http://www.xtcmotorsports.net/pp/install)

**Please read the instructions fully and familiarize yourself with the components before starting the install.**

### Quick Start

Remove the seats and center channel plastics

Run the long cable from the terminal strip on the fire wall to the battery. It runs down the fire wall along the factory wire harness between the seats and to the battery as shown.



Attach the red cable that was run to the terminal that is marked battery

Using the self tapping screws attach the circuit breaker next to the battery

Attach the red cable to the circuit breaker

Attach the short red cable from the circuit breaker to the positive post on the battery.

Using the supplied cable ties secure the cable away from any hot or moving parts.

Attach the black ground cable to the terminal marked ground



Remove the bolt from the fan sub frame and attach ground wire and reinstall.

Re install the interior of the car.

Cables and switches above can be purchased at [www.xtcpowerproducts.com](http://www.xtcpowerproducts.com)

We can also be reached at [Support@xtcpowerproducts.com](mailto:Support@xtcpowerproducts.com). Please visit our website at [www.xtcpowerproducts.com](http://www.xtcpowerproducts.com)

XTC Power Products  
A Division of XTC Motorsports LLC  
380 E Comstock Dr  
Chandler, AZ 85225  
480-558-8588  
[www.xtcpowerproducts.com](http://www.xtcpowerproducts.com)  
Copyright © 2023 XTC Motorsports LLC, All Rights Reserved